


EE450121 PROgrammer2 Update

This update to your PROgrammer2 will allow you to program both the 510R and 850R ESCs (if both are still equipped with the factory installed firmware). It also makes the currently installed ESC and PROgrammer2 version visible in the “Firmware Version” window of the program.

NOTE: All PROgrammer2 devices currently in production have this updated firmware installed from the factory.

1. Download and save update file EE450121_up (included in the compressed file).
2. Open the Blackbox Link 2.1 program.
3. Plug a USB-to-mini USB cable into an available USB port on your PC and into your PROgrammer2’s USB port. The connection will be verified by a “USB Connection” green light.
4. Select “Program Box” to update the PROgrammer2. During this first PROgrammer2 update, you will encounter the following message:



Click OK, then unplug the mini-USB connector from the PROgrammer2, and immediately plug it back in. The “Program Box Connection” green light will illuminate.

5. Click “Select” to choose the EE450121_up file. Double-click the file or click “open” and the file will automatically install.
6. The newly installed firmware file number will now appear in the “Firmware Version” window and signals that the process is complete. This, and all future update file names, will now appear in this window.
7. Disconnect the mini-USB connector from the PROgrammer2.
8. Your PROgrammer2 is now updated and ready to use with both your 510R and 850R ESCs.